

Emergency Shear Valves

A0060 Underpump Emergency Valve





Cast Iron

Available with Stainless Steel Body and Top for E85, DEF, ULSD, & Biodiesel Blends up to B100

The Emco Wheaton A0060 Emergency Shear Valve incorporates a replaceable shear section and a heat sensitive fusible link assembly. The valve can be manually operated to facilitate dispenser maintenance and incorporates a $^{3}/_{8}$ " test port. The closing poppet assembly is positioned out of the fuel flow path to minimize pressure drop. The A0060 utilizes a standard three boss mounting arrangement. Available in single or double poppet variants. Cast iron versions are powder coated.



■ UL Listed MH6518
ATEX FTZU 14 ATEX 0204

Material

Body: Cast Iron or Stainless Steel Spring: Stainless Steel Seal: Viton $^{\circledR}$

Viton® is a registered trademark of The Chemours Company

Model No. Cast Iron	Model No. Stainless Steel	Description	Inlet	Outlet	Cast Iron Lbs.	SST Lbs.	A	В
A0060-002	A0060-002S	1 ¹ /2" Single Poppet	Female	Male	5.7	6.4	6.9"	2.2"
* A0060-003	A0060-003S	1 ¹ /2" Single Poppet	Female	Female	5.6	6.3	6.7"	1.7"
A0060-015	A0060-015S	1 ¹ /2" Single Poppet	Female BSPT	Male BSPT	5.7	6.4	7.9"	3.2"
A0060-016	A0060-016S	1 ¹ /2" Single Poppet	Female BSPT	Female BSPT	5.6	6.3	6.9"	2.2"
A0060-022	A0060-022S	1 ¹ /2" Double Poppet	Female	Male	5.8	6.7	7.9"	3.2"
* A0060-023	A0060-023S	1 ¹ /2" Double Poppet	Female	Female	5.7	6.4	6.9"	2.2"
A0060-025	A0060-025S	1 ¹ /2" Double Poppet	Female BSPT	Male BSPT	5.8	6.7	7.9"	3.2"
A0060-026	A0060-026S	1 ¹ /2" Double Poppet	Female BSPT	Female BSPT	5.7	6.4	6.9"	2.2"

^{*}Most common variant

Replacement Parts

Part No.	For	Part No.	For			Cast Iron	SST
Cast Iron	Use On	Stainless Steel	Use On	Description	Outlet	Lbs.	Lbs.
492938	A0060-002	4929385	A0060-002S	1 ¹ /2" Replacement Top; 1 Poppet	Male	2.2	2.5
492939	A0060-003	492939S	A0060-003S	1 ¹ /2" Replacement Top; 1 Poppet	Female	2.3	2.6
493885	A0060-016	493885S	A0060-016S	1 ¹ /2" Replacement Top; 1 Poppet	Female BSPT	1.4	1.6
493886	A0060-015	493886S	A0060-015S	1 ¹ /2" Replacement Top; 1 Poppet	Male BSPT	1.6	1.8
493887	A0060-022	493887S	A0060-022S	1 ¹ /2" Replacement Top; 2 Poppets	Male	2.7	3.0
493888	A0060-023	493888S	A0060-023S	1 ¹ /2" Replacement Top; 2 Poppets	Female	2.7	3.0
493889	A0060-025	4938895	A0060-025S	1 ¹ /2" Replacement Top; 2 Poppets	Male BSPT	1.6	1.8
493890	A0060-026	493890S	A0060-026S	1 ¹ /2" Replacement Top; 2 Poppets	Female BSPT	1.6	1.8
492963K				Fusible Link Kit		0.2	
564036				Control Arm			
A0065-001				A0060 Stabilizer Bar Mounting Kit		3.8	